

## KEW 2433 - Leakage Clampmeter

KEW 2433 - Leakage Clamp Meters

Rating: Not Rated Yet

[Ask a question about this product](#)

Manufacturer [KYORITSU](#)

Description

- Frequency Selector Switch to eliminate the effect of harmonics.
- Three AC current ranges:40mA/400mA/400A.
- Resolution 0.01mA.

## Specification:

|   |  |
|---|--|
| AC A (50/60Hz)                          | 40/400mA/400A<br>±1%rdg±5dgt (40/400mA)<br>±1%rdg±5dgt (0 - 350A)<br>±2%rdg (350.1 - 399.9A)   |
| AC A (WIDE)                             | 40/400mA/400A<br>±2.5%rdg±10dgt [20Hz - 1kHz] (40/400mA)<br>±2.5%rdg±10dgt [40Hz - 1kHz] (0 - 350A)<br>±5%rdg [40Hz - 1kHz] (350.1 - 399.9A) |
| Maximum circuit voltage                 | 600V AC/DC (between line/neutral)<br>300V AC/DC (against earth)  |
| Conductor size                          | Ø40mm max.   |
| Frequency response                      | 20Hz - 1kHz (40Hz - 1kHz:400A)   |
| Effect of External Stray Magnetic Field | 10mA AC approx. in proximity to a 15mm-dia conductor carrying 100A AC  |
| Safety Standard                         | IEC 61010-1 CAT III 300V Pollution Degree 2<br>IEC 61010-2-032   |
| Response Time                           | Approx. 2 seconds  |
| Power source                            | Two R03 or equivalent (DC1.5V) batteries   |
| Dimensions                              | 185(L) x 81(W) x 32(D)mm   |
| Weight                                  | 270g approx.   |
| Included Accessories                    | 9097 (Carrying Case)<br>R03 (1.5V) x 2<br>Instruction Manual   |